

Serial & Parallel ExpressCards

SSPXP, DSPXP, QSPXP & SPPXP Series



Performance Line Technology

ExpressCard technology is emerging with faster speeds and better efficiency than the typical PCMCIA and PC Cards, connecting high-bandwidth peripherals to notebooks and other portables. The ExpressCard's credit-card like format gives way to a smaller, faster and more desktop-friendly format.

Gone are the days of laptops manufactured with PC Card slots and are swapped out with smaller, slimmer and thinner ExpressCard portals. Quatech's Serial ExpressCard line supersedes older technology and are engineered for new laptop models.

Quatech's ExpressCards are designed in the smallest form factor -34. ExpressCard 34 is compatible with all ExpressCard slots - 34/54.

Quatech's ExpressCard solutions accommodate I/O expansion and connectivity to serial and parallel devices in mobile laptop applications.

Available in one, two and four port serial configurations and one parallel port configuration, the ExpressCards offer easy-to-upgrade PC Card technologies, while integrating popular external peripheral functionality via ExpressCard module form-factor.

The PXP series was designed with a PCI Express (PCIe) interface rather than using USB controller interfaces.

Advantages of a PCIe-based ExpressCard design are in the interface to the laptop's motherboard. The PCIe bus interface is the successor to the PCI bus, which in turn was the successor to the ISA bus to which built-in ports were originally attached. As such, the ExpressCard adapter design utilizes a PCIe-based design and can still directly use I/O space addresses and interrupts, thus more closely emulating built-in ports than can be done via USB-based design. Moreover, because there's no USB stack for the drivers to contend with, throughput can be higher and latency will be lower (considerably so in many cases).

Due to improved data transfer rate, the ExpressCard is considerably more efficient for multi-tasking operations. The PXP series support data rates of up to 921.6Kbps, which provides steady flow of data throughput.

Quatech's PXP series is a great solution to connect with existing peripherals and maintain compatibility and functionality with their current application software.

Quatech 34mm Expresscards can be used in either 34 or 54mm Expresscard slots. As an added feature, Quatech includes their Model ADP-XP54 Expresscard 54mm adapter for 34mm cards with every shipment to improve fit and durability of the 34mm cards in the larger 54mm slots.

Quatech also sells and supports other ExpressCard connectivity products, including hard drive eSATA 2.0 and Ethernet configurations.

Model Selection Guide

Model No.	Description
SSPXP-100	1 port performance PCIe-based RS-232 serial ExpressCard
DSPXP-100	2 port performance PCIe-based RS-232 serial ExpressCard
QSPXP-100	4 port performance PCIe based RS-232 serial ExpressCard
SSPXP-200/300	1 port performance PCIe-based RS-422/485 serial ExpressCard
DSPXP-200/300	2 port performance PCIe-based RS-422/485 serial ExpressCard
QSPXP-200/300	4 port performance PCIe based RS-422/485 serial ExpressCard
SPPXP-100	1 high performance PCIe-based EPP parallel port ExpressCard

For more information, please visit www.Quatech.com/catalog/expresscard_performance.php



KEY FEATURES

- New generation of I/O expansion for notebooks
- Adds 1, 2 or 4 high-speed serial ports; 1 true parallel port
- Support PCI Express Base Specification Revision 1.1a
- Installs in any ExpressCard slot
- Built-in 1024-byte FIFOs buffers increase data transmit/receive speed
- Baud rates up to 921.6kbps
- Hot plugging and hot swapping features
- High speed ExpressCard with plug-n-play
- Supports Windows XP/Vista/7 operating systems
- 34mm ExpressCards include ADP-XP54 54mm adapter

PCIe-based Serial ExpressCards (SSPXP, DSPXP, QSPXP)

	Bus Interface	ExpressCard Standard, PCI Express-based Designs Specification, Revision 1.1 compliant interface
	OS Support	Windows XP/Vista/7
	Baud Rates	921.6kbps per port
	Serial Ports	SSPXP: 1 DSPXP: 2 QSPXP:4
	UARTS	16450/550/750-compatible register set
	Data FIFO	1024-byte
	Data Bits	Supports 5, 6, 7, 8; Supports even, odd, mark, space & no parity; Supports 1, 1.5 & 2 stop bits
	SSPXP/DSPXP-100	TIA-232-F (RS-232) compliant
	SSPXP/DSPXP-200/300	TIA-422-B (RS-422) & TIA-485-A (RS-485) compliant
	200/300 Series	<ul style="list-style-type: none"> ● Supports full-duplex and RTS, DTR or automatic transmitter control half-duplex ● Selectable receiver control (echo/no echo) ● Selectable RTS/CTS, TxCLK/RxCLK or loopback auxiliary data pair ● Full fail-safe (open and short) 1/8 load receivers
	Warranty	5 years

PCIe-based Parallel ExpressCards (SPPXP)

	Bus Interface	ExpressCard Standard, PCI Express-based Design Specification, Revision 1.1 compliant interface																																	
	OS Support	Windows XP/Vista/7																																	
	Parallel Ports	SPPXP: 1																																	
	Modes	EPP Mode, Standard Unidirectional Parallel Port Mode, Standard Bidirectional Parallel Port Mode																																	
	SPPXP-100 Series	<ul style="list-style-type: none"> ● IEEE Standard, 1284-2000 compliant ● Supports compatibility (Centronics), Bi-directional (PS/2), ECP and EPP modes ● 2048-byte FIFO (ECP mode only) ● Supports RLE decompression (ECP mode only) ● Uses the Windows system-supplied parallel drivers 																																	
	Connectors	<table style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 50%;">PIN 1: STROBE</td> <td style="width: 50%;">PIN 18: GND</td> </tr> <tr> <td>PIN 2: D0</td> <td>PIN 19: GND</td> </tr> <tr> <td>PIN 3: D1</td> <td>PIN 20: GND</td> </tr> <tr> <td>PIN 4: D2</td> <td>PIN 21: GND</td> </tr> <tr> <td>PIN 5: D3</td> <td>PIN 22: GND</td> </tr> <tr> <td>PIN 6: D4</td> <td>PIN 23: GND</td> </tr> <tr> <td>PIN 7: D5</td> <td>PIN 24: GND</td> </tr> <tr> <td>PIN 8: D6</td> <td>PIN 25: GND</td> </tr> <tr> <td>PIN 9: D7</td> <td></td> </tr> <tr> <td>PIN 10: ACK</td> <td></td> </tr> <tr> <td>PIN 11: BUSY</td> <td></td> </tr> <tr> <td>PIN 12: PERROR</td> <td></td> </tr> <tr> <td>PIN 13: SELECTIN</td> <td></td> </tr> <tr> <td>PIN 14: AUTOFEED</td> <td></td> </tr> <tr> <td>PIN 15: NFAULT</td> <td></td> </tr> <tr> <td>PIN 16: INT</td> <td></td> </tr> <tr> <td>PIN 17: SELECT</td> <td></td> </tr> </table>	PIN 1: STROBE	PIN 18: GND	PIN 2: D0	PIN 19: GND	PIN 3: D1	PIN 20: GND	PIN 4: D2	PIN 21: GND	PIN 5: D3	PIN 22: GND	PIN 6: D4	PIN 23: GND	PIN 7: D5	PIN 24: GND	PIN 8: D6	PIN 25: GND	PIN 9: D7		PIN 10: ACK		PIN 11: BUSY		PIN 12: PERROR		PIN 13: SELECTIN		PIN 14: AUTOFEED		PIN 15: NFAULT		PIN 16: INT		PIN 17: SELECT
PIN 1: STROBE	PIN 18: GND																																		
PIN 2: D0	PIN 19: GND																																		
PIN 3: D1	PIN 20: GND																																		
PIN 4: D2	PIN 21: GND																																		
PIN 5: D3	PIN 22: GND																																		
PIN 6: D4	PIN 23: GND																																		
PIN 7: D5	PIN 24: GND																																		
PIN 8: D6	PIN 25: GND																																		
PIN 9: D7																																			
PIN 10: ACK																																			
PIN 11: BUSY																																			
PIN 12: PERROR																																			
PIN 13: SELECTIN																																			
PIN 14: AUTOFEED																																			
PIN 15: NFAULT																																			
PIN 16: INT																																			
PIN 17: SELECT																																			
Warranty	5 years																																		

ExpressCard 54mm adapter for 34mm cards (ADP-XP54)

	Features	
		<ul style="list-style-type: none"> ● Enables Quatech 34mm Expresscards to be used in either 34 or 54mm Expresscard slots. ● Included with every shipment to improve fit and durability of the 34mm cards in the larger 54mm slots. ● ADP-XP54 improves the ability of the card to withstand normal or accidental stress and not dislodge from the slot.
	Warranty	1 year

QUATECH
A DPAC TECHNOLOGIES COMPANY

5675 Hudson Industrial Parkway Hudson, OH 44236

1.800.553.1170 www.quatech.com