

## **PNP** Darlington Transistor

This device is designed for applications requiring extremely high current gain at currents to 800 mA. Sourced from Process 61. See MPSA64 for characteristics.

#### **Absolute Maximum Ratings\*** TA = 25°C unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>CES</sub>	Collector-Emitter Voltage	30	V
V <sub>CBO</sub>	Collector-Base Voltage	30	V
V <sub>EBO</sub>	Emitter-Base Voltage	10	V
I <sub>C</sub>	Collector Current - Continuous	1.2	А
T <sub>J</sub> , T <sub>stg</sub>	Operating and Storage Junction Temperature Range	-55 to +150	°C

\*These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

## NOTES:

1) These ratings are based on a maximum junction temperature of 150 degrees C.
2) These are steady state limits. The factory should be consulted on applications involving pulsed or low duty cycle operations.

#### Thermal Characteristics TA = 25°C unless otherwise noted

Symbol	Characteristic	Мах		Units	
		MPSA65	*MMBTA65	**PZTA65	
PD	Total Device Dissipation Derate above 25°C	625 5.0	350 2.8	1,000 8.0	mW mW/°C
$R_{\theta JC}$	Thermal Resistance, Junction to Case	83.3			°C/W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	200	357	125	°C/W

\*Device mounted on FR-4 PCB 1.6" X 1.6" X 0.06."

\*\* Device mounted on FR-4 PCB 36 mm X 18 mm X 1.5 mm; mounting pad for the collector lead min. 6 cm<sup>2</sup>.

# PNP Darlington Transistor (continued)

continued)
------------

Symbol	Parameter	Test Conditions	Min	Мах	Units
0 == 0.14					
OFF CHA	ARACTERISTICS				
V <sub>(BR)CES</sub>	Collector-Emitter Breakdown Voltage	$I_{C} = 100 \ \mu A, \ I_{B} = 0$	30		V
I <sub>СВО</sub>	Collector-Cutoff Current	$V_{CB} = 30 \text{ V}, I_E = 0$		100	nA
I <sub>EBO</sub>	Emitter-Cutoff Current	$V_{EB} = 8.0 V, I_{C} = 0$		100	nA

h <sub>FE</sub>	DC Current Gain	$I_{C} = 10 \text{ mA}, V_{CE} = 5.0 \text{ V}$	50,000		
		$I_{C} = 100 \text{ mA}, V_{CE} = 5.0 \text{ V}$	20,000		
V <sub>CE(sat)</sub>	Collector-Emitter Saturation Voltage	$I_{\rm C}$ = 100 mA, $I_{\rm B}$ = 0.1 mA		1.5	V
V <sub>BE(on)</sub>	Base-Emitter On Voltage	$I_{C}$ = 100 mA, $V_{CE}$ = 5.0 V		2.0	V

### SMALL SIGNAL CHARACTERISTICS

-

-

-

f <sub>T</sub>	Current Gain - Bandwidth Product	$I_{C} = 10 \text{ mA}, V_{CE} = 5.0 \text{ V},$ f = 100 MHz	100	MHz
----------------	----------------------------------	---	-----	-----

\*Pulse Test: Pulse Width  $\leq 300~\mu s,~\text{Duty}~\text{Cycle} \leq 2.0\%$ 

#### TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™ Bottomless™ CoolFET™ CROSSVOLT™ DOME™ E<sup>2</sup>CMOS<sup>™</sup> EnSigna™ FACT™ FACT Quiet Series<sup>™</sup> FAST<sup>®</sup>

FASTr™ GlobalOptoisolator™ GTO™ HiSeC™ **ISOPLANAR™** MICROWIRE™ OPTOLOGIC™ **OPTOPLANAR™** PACMAN™ POP™

PowerTrench<sup>®</sup> QFET™ QS™ QT Optoelectronics<sup>™</sup> Quiet Series<sup>™</sup> SILENT SWITCHER® SMART START™ SuperSOT<sup>™</sup>-3 SuperSOT<sup>™</sup>-6 SuperSOT<sup>™</sup>-8

SyncFET™ TinyLogic™ UHC™ VCX™

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### PRODUCT STATUS DEFINITIONS

**Definition of Terms** 

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.
	1	Rev G