SDLS090 - OCTOBER 1976 - REVISED MARCH 1988

- Contains Eight Flip-Flops With Single-Rail Outputs
- Buffered Clock and Direct Clear Inputs
- Individual Data Input to Each Flip-Flop
- Applications Include: Buffer/Storage Registers Shift Registers Pattern Generators

description

These monolithic, positive-edge-triggered flipflops utilize TTL circuitry to implement D-type flip-flop logic with a direct clear input.

Information at the D inputs meeting the setup time requirements is transferred to the Q outputs on the positive-going edge of the clock pulse. Clock triggering occurs at a particular voltage level and is not directly related to the transition time of the positive-going pulse. When the clock input is at either the high or low level, the D input signal has no effect ar the output.


These flip-flops are guaranteed to respond to clock frequencies ranging form 0 to 30 megahertz while maximum clock frequency is typically 40 megahertz. Typical power dissipation is 39 milliwatts per flip-flop for the '273 and 10 milliwatts for the 'LS273.

FUNCTION TABLE (each flip-flop)


(odon nip nop)										
	NPUTS		OUTPUT							
CLEAR	CLOCK	D	Q							
L	Х	Х	L							
н	\uparrow	Н	н							
н	\uparrow	L	L							
н	L	Х	Q ₀							

CLR [1	U	20] v _{cc}
1Q [2		19] 8Q
1D [3		18] 8D
2D [4		17]7D
2Q [5		16] 7Q
3Q [6		15] 6Q
3D [7		14] 6D
4D [8		13] 5D
4Q [9		12] 5Q
GND [10		11] CLK

SN54LS273 . . . FK PACKAGE (TOP VIEW)



logic symbol[†]




[†] This symbol is in accordance with ANSI/IEEE Std. 91-1984 and IEC Publication 617-12. Pin numbers shown are for the DW, J, N, and W packages.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

SDLS090 - OCTOBER 1976 - REVISED MARCH 1988

schematics of inputs and outputs



Pin numbers shown are for the DW, J, N, and W packages.



19

8Q

SDLS090 - OCTOBER 1976 - REVISED MARCH 1988

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, V _{CC} (see Note 1)	
Input voltage	5.5 V
Operating free-air temperature range, T _A : SN54273	5°C to 125°C
SN74273	0°C to 70°C
Storage temperature range	5°C to 150°C

NOTE 1: Voltage values are with respect to network ground terminal.

recommended operating conditions

			SN54273	54273 SN74273			UNIT	
		MIN	NOM	MAX	MIN	NOM	MAX	UNIT
Supply voltage, V _{CC}		4.5	5	5.5	4.75	5	5.25	V
High-level output current, IOH				-800			-800	μA
Low-level output current, IOL			16			16	mA	
Clock frequency, f _{clock}	0		30	0		30	MHz	
Width of clock or clear pulse, t _W		16.5			16.5			ns
Cotup time t	Data input	20↑			20↑			
Setup time, t _{su}	Clear inactive state	25↑			25↑			ns
Data hold time, t _h	5↑			5↑			ns	
Operating free-air temperature, TA		-55		125	0		70	°C

 \uparrow The arrow indicates that the rising edge of the clock pulse is used for reference.

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

	PARAMETER		TEST C	ONDITIONS [†]	MIN	TYP‡	MAX	UNIT
VIH	High-level input voltage				2			V
VIL	Low-level input voltage						0.8	V
VIK	Input clamp voltage		$V_{CC} = MIN,$	lj = -12 mA			-1.5	V
∨он	High-level output voltage	$V_{CC} = MIN,$ $V_{IL} = 0.8 V,$	V _{IH} = 2 V, I _{OH} = −800 μA	2.4	3.4		V	
V _{OL}	Low-level output voltage		V _{CC} = MIN, V _{IL} = 0.8 V,	V _{IH} = 2 V, I _{OH} = 16 mA			0.4	V
Ιį	Input current at maximum input voltag	е	V _{CC} = MAX,	V _I = 5.5 V			1	mA
1	High lovel input ourrept	Clear		V ₁ = 2.4 V			80	
ЧН	High-level input current	Clock or D	$V_{CC} = MAX,$	v = 2.4 v			40	μA
1	Low loval input ourrant	Clear	VCC = MAX,	$V_{I} = 0.4 V$			-3.2	mA
۱L	Low-level input current	Low-level input current Clock or D		v] = 0.4 v			-1.6	ША
IOS	Short-circuit output current§		$V_{CC} = MAX$		-18		-57	mA
ICC	Supply current		V _{CC} = MAX,	See Note 2		62	94	mA

[†] For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

[‡] All typical values are at V_{CC} = 5 V, T_A = 25° C.

§ Not more than one output should be shorted at a time.

NOTE 2: With all outputs open and 4.5 V applied to all data and clear inputs, I_{CC} is measured after a momentary ground, then 4.5 V, is applied to clock.



SDLS090 - OCTOBER 1976 - REVISED MARCH 1988

switching characteristics, V_{CC} = 5 V, T_A = 25°C

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
fmax	Maximum clock frequency		30	40		MHz
^t PHL	Propagation delay time, high-to-low-level output from clear	CL = 15 pF,		18	27	ns
^t PLH	Propagation delay time, low-to-high-level output from clock	R _L = 400 Ω, See Note 3		17	27	ns
^t PHL	Propagation delay time, high-to-low-level output from clock			18	27	ns

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, V _{CC} (see Note 1)	
Operating free-air temperature range, T _A : SN54LS273 SN74LS273	-55°C to 125°C
Storage temperature range	

NOTE 1: Voltage values are with respect to network ground terminal.

recommended operating conditions

	SI	SN54LS273			SN74LS273		
	MIN	NOM	MAX	MIN	NOM	MAX 5.25 -400 8 30	UNIT
	4.5	5	5.5	4.75	5	5.25	V
High-level output current, I _{OH}						-400	μΑ
Low-level output current, IOL						8	mA
Clock frequency, f _{clock}				0		30	MHz
	20			20			ns
Data input	20↑			20↑			
Clear inactive state	20 20 20↑ 20↑ tate 25↑	ns					
Data hold time, th				5↑			ns
	-55		125	0		70	°C
		MIN 4.5 0 20 Data input 20↑ Clear inactive state 25↑ 5↑	MIN NOM 4.5 5 0 20 Data input 20^1 Clear inactive state 25^1 51	MIN NOM MAX 4.5 5 5.5 -400 -400 0 30 20 - Data input 20^1 Clear inactive state 25^1 5^1 -	MIN NOM MAX MIN 4.5 5 5.5 4.75 4.5 5 5.5 4.75 -400 -400 -400 0 -400 -400 0 30 0 20 20 20 Data input 20^1 20^1 Clear inactive state 25 [↑] 25 [↑]	MIN NOM MAX MIN NOM 4.5 5 5.5 4.75 5 -400 -400 -400 -400 -400	MIN NOM MAX MIN NOM MAX 4.5 5 5.5 4.75 5.5 5.25 -400 -400 -400 -400 -400 400 400 400 -400 -400 400 400 400 400 -400

 \uparrow The arrow indicates that the rising edge of the clock pulse is used for reference.



SDLS090 - OCTOBER 1976 - REVISED MARCH 1988

		TEST CONDITIONST			S	N54LS27	'3	SI	N74LS27	3	
	PARAMETER	IES	MIN	TYP‡	MAX	MIN	TYP‡	MAX	UNIT		
VIH	High-level input voltage				2			2			V
VIL	Low-level input voltage						0.7			0.8	V
VIK	Input clamp voltage	V _{CC} = MIN,	lı = – 18 mA				-1.5			-1.5	V
VOH	High-level output voltage	V _{CC} = MIN, V _{IL} = V _{IL} max,	V _{IH} = 2 V, I _{OH} = -400	μΑ	2.5	3.4		2.7	3.4		V
Vai		V _{CC} = MIN,	VIH = 2 V,	$I_{OL} = 4 \text{ mA}$		0.25	0.4		0.25	0.4	V
VOL	Low-level output voltage	$V_{IL} = V_{IL}max$,		$I_{OL} = 8 \text{ mA}$					0.35	0.5	v
II.	Input current at maximum input voltage	V _{CC} = MAX,	V _I = 7 V				0.1			0.1	mA
IIН	High-level input current	V _{CC} = MAX,	V _I = 2.7 V				20			20	μΑ
١ _{IL}	Low-level input current	V _{CC} = MAX,	V _I = 0.4 V				-0.4			-0.4	mA
IOS	Short-circuit output current§	V _{CC} = MAX			-20		-100	-20		-100	mA
ICC	Supply current	V _{CC} = MAX,	See Note 2			17	27		17	27	mA

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

[†] For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.

[‡] All typical values are at $V_{CC} = 5 V$, $T_A = 25^{\circ}C$.

§ Not more than one output should be shorted at a time and duration of short circuit should not exceed one second.

NOTE 2: With all outputs open and 4.5 V applied to all data and clear inputs, I_{CC} is measured after a momentary ground, then 4.5 V, is applied to clock.

switching characteristics, V_{CC} = 5 V, T_A = 25° C

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
fmax	Maximum clock frequency		30	40		MHz
^t PHL	Propagation delay time, high-to-low-level output from clear	C _L = 15 pF, R _I = 2 kΩ,		18	27	ns
^t PLH	Propagation delay time, low-to-high-level output from clock	$R_L = 2 R_{32}$, See Note 3		17	27	ns
^t PHL	Propagation delay time, high-to-low-level output from clock			18	27	ns

NOTE 3: Load circuits and voltage waveforms are shown in Section 1.




TEXAS INSTRUMENTS www.ti.com

TAPE AND REEL INFORMATION





QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE




*All dimensions are nominal												
Device		Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74LS273DWR	SOIC	DW	20	2000	330.0	24.4	10.8	13.0	2.7	12.0	24.0	Q1
SN74LS273NSR	SO	NS	20	2000	330.0	24.4	8.2	13.0	2.5	12.0	24.0	Q1



PACKAGE MATERIALS INFORMATION

5-Aug-2008



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74LS273DWR	SOIC	DW	20	2000	346.0	346.0	41.0
SN74LS273NSR	SO	NS	20	2000	346.0	346.0	41.0

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DLP® Products	www.dlp.com	Communications and Telecom	www.ti.com/communications
DSP	dsp.ti.com	Computers and Peripherals	www.ti.com/computers
Clocks and Timers	www.ti.com/clocks	Consumer Electronics	www.ti.com/consumer-apps
Interface	interface.ti.com	Energy	www.ti.com/energy
Logic	logic.ti.com	Industrial	www.ti.com/industrial
Power Mgmt	power.ti.com	Medical	www.ti.com/medical
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
RFID	www.ti-rfid.com	Space, Avionics & Defense	www.ti.com/space-avionics-defense
RF/IF and ZigBee® Solutions	www.ti.com/lprf	Video and Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless-apps

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2010, Texas Instruments Incorporated