


### LOW-POWER SINGLE INVERTER GATE

Check for Samples: SN74AUP1G04

### **FEATURES**

- Available in the Texas Instruments NanoStar™ Package
- Low Static-Power Consumption (I<sub>CC</sub> = 0.9 μA Max)
- Low Dynamic-Power Consumption (C<sub>pd</sub> = 4.1 pF Typ at 3.3 V)
- Low Input Capacitance (C<sub>i</sub> = 1.5 pF Typ)
- Low Noise Overshoot and Undershoot <10% of V<sub>CC</sub>
- I<sub>off</sub> Supports Partial-Power-Down Mode Operation
- Input Hysteresis Allows Slow Input Transition and Better Switching Noise Immunity at the Input (V<sub>hvs</sub> = 250 mV Typ at 3.3 V)

- Wide Operating V<sub>CC</sub> Range of 0.8 V to 3.6 V
- Optimized for 3.3-V Operation
- 3.6-V I/O Tolerant to Support Mixed-Mode Signal Operation
- t<sub>pd</sub> = 3.9 ns Max at 3.3 V
- Suitable for Point-to-Point Applications
- Latch-Up Performance Exceeds 100 mA Per JESD 78, Class II
- ESD Performance Tested Per JESD 22
  - 2000-V Human-Body Model (A114-B, Class II)
  - 1000-V Charged-Device Model (C101)



N.C. - No internal connection.

DNU - Do not use

See mechancial drawings for dimensions.


#### DESCRIPTION/ORDERING INFORMATION


The AUP family is TI's premier solution to the industry's low power needs in battery-powered portable applications. This family ensures a very low static and dynamic power consumption across the entire  $V_{CC}$  range of 0.8 V to 3.6 V, resulting in an increased battery life. This product also maintains excellent signal integrity (see Figure 1 and Figure 2).

M

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.










Figure 2. Excellent Signal Integrity

### Figure 1. AUP – The Lowest-Power Family

This single inverter gate performs the Boolean function Y = A.

NanoStar™ package technology is a major breakthrough in IC packaging concepts, using the die as the package.

This device is fully specified for partial-power-down applications using  $I_{\text{off}}$ . The  $I_{\text{off}}$  circuitry disables the outputs, preventing damaging current backflow through the device when it is powered down.

### ORDERING INFORMATION(1)

T <sub>A</sub>	PACKAGE <sup>(2)</sup>		ORDERABLE PART NUMBER	TOP-SIDE Marking <sup>(3)</sup>
	NanoStar™ – WCSP (DSBGA) 0.23-mm large bump – YFP	Reel of 3000	SN74AUP1G04YFPR	HC_
	QFN – DRY	Reel of 5000	SN74AUP1G04DRYR	HC
	QFN – DRY	Reel of 5000	SN74AUP1G04DRY2 <sup>(4)</sup>	HC
–40°C to 85°C	uQFN – DSF	Reel of 5000	SN74AUP1G04DSFR	HC
	SOT (SOT-23) – DBV	Reel of 3000	SN74AUP1G04DBVR	H04_
	SOT (SC-70) - DCK	Reel of 3000	SN74AUP1G04DCKR	HC_
	SOT (SOT-553) – DRL	Reel of 4000	SN74AUP1G04DRLR	HC_

<sup>(1)</sup> For the most current package and ordering information, see the Package Option Addendum at the end of this document, or see the TI web site at www.ti.com.

#### **FUNCTION TABLE**

INPUT A	INPUT B
Н	L
L	Н

Submit Documentation Feedback

<sup>(2)</sup> Package drawings, thermal data, and symbolization are available at www.ti.com/packaging.


<sup>(3)</sup> DBV/DCK/DRL: The actual top-side marking has one additional character that designates the wafer fab/assembly site. YFP: The actual top-side marking has three preceding characters to denote year, month, and sequence code, and one following character to designate the wafer fab/assembly site. Pin 1 identifier indicates solder-bump composition (1 = SnPb, • = Pb-free).

<sup>(4)</sup> Pin 1 orientation at quadrant 3 in Tape.




### LOGIC DIAGRAM (POSITIVE LOGIC)

(DBV, DCK, DRL, and DRY Packages)



### (YFP Package)



### ABSOLUTE MAXIMUM RATINGS(1)

over operating free-air temperature range (unless otherwise noted)

			MIN	MAX	UNIT
$V_{CC}$	Supply voltage range		-0.5	4.6	V
VI	Input voltage range <sup>(2)</sup>		-0.5	4.6	V
Vo	Voltage range applied to any output in the high-impeda	nce or power-off state <sup>(2)</sup>	-0.5	4.6	V
Vo	Output voltage range in the high or low state <sup>(2)</sup>		-0.5	V <sub>CC</sub> + 0.5	V
I <sub>IK</sub>	Input clamp current	V <sub>1</sub> < 0		-50	mA
I <sub>OK</sub>	Output clamp current	V <sub>O</sub> < 0		-50	mA
Io	Continuous output current		±20	mA	
	Continuous current through V <sub>CC</sub> or GND			±50	mA
		DBV package		206	
		DCK package		252	
0	Dealers thereal investigation (3)	DRL package		142	0000
$\theta_{JA}$	Package thermal impedance (3)	DSF package		300	°C/W
		DRY package		234	
		YFP package		132	
T <sub>stg</sub>	Storage temperature range		-65	150	°C

<sup>(1)</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(3) The package thermal impedance is calculated in accordance with JESD 51-7.

<sup>(2)</sup> The input negative-voltage and output voltage ratings may be exceeded if the input and output current ratings are observed.





## RECOMMENDED OPERATING CONDITIONS(1)

			MIN	MAX	UNIT	
V <sub>CC</sub>	Supply voltage		0.8	3.6	V	
		V <sub>CC</sub> = 0.8 V	V <sub>CC</sub>			
\	High level inner water	V <sub>CC</sub> = 1.1 V to 1.95 V	0.65 × V <sub>CC</sub>		.,	
$V_{IH}$	High-level input voltage	V <sub>CC</sub> = 2.3 V to 2.7 V	1.6		V	
		V <sub>CC</sub> = 3 V to 3.6 V	2			
		V <sub>CC</sub> = 0.8 V		0		
\	Law layed in a trade as	V <sub>CC</sub> = 1.1 V to 1.95 V	0.3	35 × V <sub>CC</sub>	V	
$V_{IL}$	Low-level input voltage	V <sub>CC</sub> = 2.3 V to 2.7 V		0.7	V	
		V <sub>CC</sub> = 3 V to 3.6 V		0.9		
VI	Input voltage		0	3.6	V	
Vo	Output voltage		0	V <sub>CC</sub>	V	
		V <sub>CC</sub> = 0.8 V		-20	μΑ	
		V <sub>CC</sub> = 1.1 V		-1.1		
	I Pale Javed autout august	V <sub>CC</sub> = 1.4 V		-1.7		
I <sub>OH</sub>	High-level output current	V <sub>CC</sub> = 1.65 V		-1.9	mA	
		V <sub>CC</sub> = 2.3 V		-3.1		
		V <sub>CC</sub> = 3 V		-4		
		V <sub>CC</sub> = 0.8 V		20	μΑ	
		V <sub>CC</sub> = 1.1 V		1.1		
	Law lawal autant annuart	V <sub>CC</sub> = 1.4 V		1.7		
l <sub>OL</sub>	Low-level output current	V <sub>CC</sub> = 1.65 V				
		V <sub>CC</sub> = 2.3 V		3.1	1	
		V <sub>CC</sub> = 3 V		4		
Δt/Δν	Input transition rise or fall rate	V <sub>CC</sub> = 0.8 V to 3.6 V		200	ns/V	
T <sub>A</sub>	Operating free-air temperature		-40	85	°C	

<sup>(1)</sup> All unused inputs of the device must be held at  $V_{CC}$  or GND to ensure proper device operation. Refer to the TI application report, Implications of Slow or Floating CMOS Inputs, literature number SCBA004.



### **ELECTRICAL CHARACTERISTICS**

over recommended operating free-air temperature range (unless otherwise noted)

DADAMETED	TEST COMPLETIONS	.,	TA	= 25°C		T <sub>A</sub> = -40°C	to 85°C	LINUT		
PARAMETER	TEST CONDITIONS	V <sub>cc</sub>	MIN	TYP	MAX	MIN	MAX	UNIT		
	I <sub>OH</sub> = -20 μA	0.8 V to 3.6 V	V <sub>CC</sub> - 0.1			V <sub>CC</sub> - 0.1				
	I <sub>OH</sub> = -1.1 mA	1.1 V	0.75 × V <sub>CC</sub>			0.7 × V <sub>CC</sub>				
	$I_{OH} = -1.7 \text{ mA}$	1.4 V	1.11			1.03				
V	I <sub>OH</sub> = −1.9 mA	1.65 V	1.32			1.3		V		
V <sub>OH</sub>	$I_{OH} = -2.3 \text{ mA}$	221/	2.05			1.97		V		
	$I_{OH} = -3.1 \text{ mA}$	2.3 V	1.9			1.85				
	$I_{OH} = -2.7 \text{ mA}$	2.1/	2.72			2.67				
	$I_{OH} = -4 \text{ mA}$	3 V	2.6			2.55				
	I <sub>OL</sub> = 20 μA	0.8 V to 3.6 V			0.1		0.1			
	I <sub>OL</sub> = 1.1 mA	1.1 V			0.3 × V <sub>CC</sub>		0.3 × V <sub>CC</sub>			
	I <sub>OL</sub> = 1.7 mA	1.4 V			0.31		0.37			
	I <sub>OL</sub> = 1.9 mA	1.65 V			0.31		0.35	.,		
$V_{OL}$	I <sub>OL</sub> = 2.3 mA	227			0.31		0.33	V		
	I <sub>OL</sub> = 3.1 mA	2.3 V			0.44 0.4					
	I <sub>OL</sub> = 2.7 mA	2.1/			0.31		0.33			
	I <sub>OL</sub> = 4 mA	3 V			0.44		0.45			
I <sub>I</sub> A input	$V_I = GND \text{ to } 3.6 \text{ V}$	0 V to 3.6 V			0.1		0.5	μΑ		
I <sub>off</sub>	$V_I$ or $V_O = 0 V$ to 3.6 V	0 V			0.2		0.6	μΑ		
ΔI <sub>off</sub>	$V_I$ or $V_O = 0 V$ to 3.6 V	0 V to 0.2 V			0.2		0.6	μA		
I <sub>CC</sub>	V <sub>I</sub> = GND or I <sub>O</sub> = 0 (V <sub>CC</sub> to 3.6 V)	0.8 V to 3.6 V			0.5		0.9	μΑ		
ΔI <sub>CC</sub>	$V_{I} = V_{CC} - 0.6 \text{ V}, I_{O} = 0$	3.3 V			40		50	μΑ		
	V = V = or GND	0 V		1.5				nΕ		
C <sub>I</sub>	$V_I = V_{CC}$ or GND	3.6 V		1.5				pF		
C <sub>o</sub>	$V_O = V_{CC}$ or GND	3.6 V		2.5				рF		

### **SWITCHING CHARACTERISTICS**

over recommended operating free-air temperature range,  $C_L = 5 \text{ pF}$  (unless otherwise noted) (see Figure 3 and Figure 4)

PARAMETER	FROM TO (OUTPUT)	V <sub>CC</sub>	T,	<sub>4</sub> = 25°C		T <sub>A</sub> = -		UNIT	
		(001701)		MIN	TYP	MAX	MIN	MAX	
		Y	0.8 V		15.6				
	t <sub>pd</sub> A		1.2 V ± 0.1 V	3.3	5.9	10.8	2.1	13.5	
			1.5 V ± 0.1 V	2.5	4.2	7	1.6	8.8	
T <sub>pd</sub>			1.8 V ± 0.15 V	2.2	3.4	5.9	1.4	7	ns
			2.5 V ± 0.2 V	1.7	2.5	4	1.3	4.9	
			3.3 V ± 0.3 V	1.4	2.1	3.2	1.2	3.9	

Copyright © 2004–2012, Texas Instruments Incorporated



### **SWITCHING CHARACTERISTICS**

over recommended operating free-air temperature range,  $C_L = 10 \text{ pF}$  (unless otherwise noted) (see Figure 3 and Figure 4)

PARAMETER	FROM	TO (OUTBUT)	V <sub>cc</sub>	T,	<sub>λ</sub> = 25°C		T <sub>A</sub> = -	40°C 5°C	UNIT
	(INPUT)	(OUTPUT)		MIN	TYP	MAX	MIN	MAX	
			0.8 V		17.7				
			1.2 V ± 0.1 V	3.9	6.9	12.2	3.1	15	
	^		1.5 V ± 0.1 V	3	5	8.1	2.5	9.9	
t <sub>pd</sub>	A		1.8 V ± 0.15 V	2.6	4	6.9	2.1	7.9	ns
			2.5 V ± 0.2 V	2.1	3	4.6	1.7	5.6	
			3.3 V ± 0.3 V	1.8	2.5	3.8	1.5	4.5	

### **SWITCHING CHARACTERISTICS**

over recommended operating free-air temperature range,  $C_L = 15 \text{ pF}$  (unless otherwise noted) (see Figure 3 and Figure 4)

PARAMETER	FROM	-	V <sub>cc</sub>	T	λ = 25°C		T <sub>A</sub> = -		UNIT
(INPUT)	(OUTPUT)		MIN	TYP	MAX	MIN	MAX		
		Y	0.8 V		19.5				
	t <sub>pd</sub> A		1.2 V ± 0.1 V	4.7	7.8	13	3.8	15.9	
			1.5 V ± 0.1 V	3.7	5.6	8.6	3.1	10.6	
<sup>t</sup> pd			1.8 V ± 0.15 V	3.2	4.6	7.4	2.6	8.5	ns
			2.5 V ± 0.2 V	2.5	3.5	5.1	2.1	6.1	
			3.3 V ± 0.3 V	2.2	2.9	4.2	1.9	5	

### **SWITCHING CHARACTERISTICS**

over recommended operating free-air temperature range, C<sub>L</sub> = 30 pF (unless otherwise noted) (see Figure 3 and Figure 4)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	V <sub>CC</sub>	T <sub>A</sub> = 25°C			T <sub>A</sub> = -40°C to 85°C		UNIT
				MIN	TYP	MAX	MIN	MAX	
		Y	0.8 V		25.4				
			1.2 V ± 0.1 V	6.8	10.4	16	6.1	19	
	Δ.		1.5 V ± 0.1 V	5.3	7.6	10.8	4.8	12.9	
<sup>t</sup> pd	A		1.8 V ± 0.15 V	4.6	6.3	9.2	4.1	10.5	ns
			2.5 V ± 0.2 V	3.6	4.8	6.5	3.3	7.6	
			3.3 V ± 0.3 V	3.2	4	5.4	2.9	6.2	

### **OPERATING CHARACTERISTICS**


 $T_{\Delta} = 25^{\circ}C$ 

	PARAMETER	TEST CONDITIONS	V <sub>cc</sub>	TYP	UNIT
		0.8 V	3.9		
	C <sub>pd</sub> Power dissipation capacitance		1.2 V ± 0.1 V	3.9	
_		f 40 MH=	1.5 V ± 0.1 V	3.9	
Cpd		f = 10 MHz	1.8 V ± 0.15 V	3.9	pF
			2.5 V ± 0.2 V	3.9	
			3.3 V ± 0.3 V	4.1	

Submit Documentation Feedback




# PARAMETER MEASUREMENT INFORMATION (Propagation Delays, Setup and Hold Times, and Pulse Width)



LOAD CIRCUIT

	V <sub>CC</sub> = 0.8 V	V <sub>cc</sub> = 1.2 V ± 0.1 V	V <sub>cc</sub> = 1.5 V ± 0.1 V	V <sub>CC</sub> = 1.8 V ± 0.15 V	$V_{\rm cc}$ = 2.5 V $\pm$ 0.2 V	V <sub>cc</sub> = 3.3 V ± 0.3 V
CL	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF
V <sub>M</sub>	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2
V <sub>I</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>




NOTES: A.  $C_L$  includes probe and jig capacitance.

- B. All input pulses are supplied by generators having the following characteristics: PRR  $\leq$  10 MHz,  $Z_{\Omega}$  = 50  $\Omega$ ,  $t_{r}/t_{r}$  = 3 ns.
- C. The outputs are measured one at a time, with one transition per measurement.
- D.  $t_{PLH}$  and  $t_{PHL}$  are the same as  $t_{pd}$ .
- E. All parameters and waveforms are not applicable to all devices.

Figure 3. Load Circuit and Voltage Waveforms




# PARAMETER MEASUREMENT INFORMATION (Enable and Disable Times)



TEST	S1
t <sub>PLZ</sub> /t <sub>PZL</sub> t <sub>PHZ</sub> /t <sub>PZH</sub>	$\begin{array}{c} 2 \times \mathbf{V_{CC}} \\ \mathbf{GND} \end{array}$

	V <sub>CC</sub> = 0.8 V	V <sub>CC</sub> = 1.2 V ± 0.1 V	V <sub>cc</sub> = 1.5 V ± 0.1 V	V <sub>cc</sub> = 1.8 V ± 0.15 V	V <sub>CC</sub> = 2.5 V ± 0.2 V	V <sub>CC</sub> = 3.3 V ± 0.3 V
CL	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF	5, 10, 15, 30 pF
V <sub>M</sub>	V <sub>CC</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2	V <sub>cc</sub> /2
V <sub>I</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	V <sub>cc</sub>	$V_{cc}$
V <sub>A</sub>	0.1 V	0.1 V	0.1 V	0.15 V	0.15 V	0.3 V



NOTES: A. C<sub>L</sub> includes probe and jig capacitance.

- B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.
- C. All input pulses are supplied by generators having the following characteristics: PRR  $\leq$  10 MHz,  $Z_{O}$  = 50  $\Omega$ ,  $t_{f}/t_{f}$  = 3 ns.
- D. The outputs are measured one at a time, with one transition per measurement.
- E.  $t_{PLZ}$  and  $t_{PHZ}$  are the same as  $t_{dis}$ .
- F.  $t_{PZL}$  and  $t_{PZH}$  are the same as  $t_{en}$ .
- G. All parameters and waveforms are not applicable to all devices.

Figure 4. Load Circuit and Voltage Waveforms

Submit Documentation Feedback





### **REVISION HISTORY**

Cł	hanges from Revision I (November 2011) to Revision J	Page
•	Revised document to fix package addendum issue.	1

Product Folder Link(s): SN74AUP1G04

# DBV (R-PDSO-G5)

# PLASTIC SMALL-OUTLINE PACKAGE



- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
- D. Falls within JEDEC MO-178 Variation AA.



# DBV (R-PDSO-G5)

# PLASTIC SMALL OUTLINE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Customers should place a note on the circuit board fabrication drawing not to alter the center solder mask defined pad.
- D. Publication IPC-7351 is recommended for alternate designs.
- E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Example stencil design based on a 50% volumetric metal load solder paste. Refer to IPC-7525 for other stencil recommendations.



# DCK (R-PDSO-G5)

# PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in millimeters.

- B. This drawing is subject to change without notice.
- C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
- D. Falls within JEDEC MO-203 variation AA.



# DCK (R-PDSO-G5)

# PLASTIC SMALL OUTLINE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Customers should place a note on the circuit board fabrication drawing not to alter the center solder mask defined pad.
- D. Publication IPC-7351 is recommended for alternate designs.
- E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Example stencil design based on a 50% volumetric metal load solder paste. Refer to IPC-7525 for other stencil recommendations.



# DRL (R-PDSO-N5)

# PLASTIC SMALL OUTLINE




- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M—1994.
- B. This drawing is subject to change without notice.
- Body dimensions do not include mold flash, interlead flash, protrusions, or gate burrs.

  Mold flash, interlead flash, protrusions, or gate burrs shall not exceed 0,15 per end or side.
- D. JEDEC package registration is pending.



# DRL (R-PDSO-N5)

### PLASTIC SMALL OUTLINE



NOTES: A. All linear dimensions are in millimeters.

- B. This drawing is subject to change without notice.
- C. Publication IPC-7351 is recommended for alternate designs.
- D. Customers should contact their board fabrication site for minimum solder mask web tolerances between signal pads.
- E. Maximum stencil thickness 0,127 mm (5 mils). All linear dimensions are in millimeters.
- F. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
- G. Side aperture dimensions over—print land for acceptable area ratio > 0.66. Customer may reduce side aperture dimensions if stencil manufacturing process allows for sufficient release at smaller opening.






NOTES: A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.

- B. This drawing is subject to change without notice.
- C. SON (Small Outline No-Lead) package configuration.
- The exposed lead frame feature on side of package may or may not be present due to alternative lead frame designs.
- E. This package complies to JEDEC MO-287 variation UFAD.
- $frac{f}{K}$  See the additional figure in the Product Data Sheet for details regarding the pin 1 identifier shape.



# DRY (S-PUSON-N6)

### PLASTIC SMALL OUTLINE NO-LEAD



- NOTES: A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Publication IPC-7351 is recommended for alternate designs.
  - D. Customers should contact their board fabrication site for minimum solder mask web tolerances between signal pads.
  - E. Maximum stencil thickness 0,127 mm (5 mils). All linear dimensions are in millimeters.
  - F. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
  - G. Side aperture dimensions over-print land for acceptable area ratio > 0.66. Customer may reduce side aperture dimensions if stencil manufacturing process allows for sufficient release at smaller opening.






NOTES: All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M—1994.

- B. This drawing is subject to change without notice.
  C. SON (Small Outline No-Lead) package configuration.
  D. This package complies to JEDEC MO-287 variation X2AAF.



DSF (S-PX2SON-N6)

PLASTIC SMALL OUTLINE NO-LEAD




- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Publication IPC-7351 is recommended for alternate designs.
- D. Customers should contact their board fabrication site for minimum solder mask web tolerances between signal pads. If 2 mil solder mask is outside PCB vendor capability, it is advised to omit solder mask.
- E. Maximum stencil thickness 0,1016 mm (4 mils). All linear dimensions are in millimeters.
- F. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
- G. Over—printing land for acceptable area ratio is not viable due to land width and bridging potential. Customer may further reduce side aperture dimensions if stencil manufacturing process allows for sufficient release at smaller opening.
- H. Suggest stencils cut with lasers such as Fiber Laser that produce the greatest positional accuracy.
- I. Component placement force should be minimized to prevent excessive paste block deformation.



# YFP (S-XBGA-N4)

### DIE-SIZE BALL GRID ARRAY



NOTES: A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.

- B. This drawing is subject to change without notice.
- C. NanoFree™ package configuration.
- The package size (Dimension D and E) of a particular device is specified in the device Product Data Sheet version of this drawing, in case it cannot be found in the product data sheet please contact a local TI representative.
- E. Reference Product Data Sheet for array population. 2 x 2 matrix pattern is shown for illustration only.
- F. This package contains Pb-free balls.

#### NanoFree is a trademark of Texas Instruments



21-May-2012

### **PACKAGING INFORMATION**

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/ Ball Finish	MSL Peak Temp <sup>(3)</sup>	Samples (Requires Login)
SN74AUP1G04DBVR	ACTIVE	SOT-23	DBV	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DBVRE4	ACTIVE	SOT-23	DBV	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DBVRG4	ACTIVE	SOT-23	DBV	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DBVT	ACTIVE	SOT-23	DBV	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DBVTE4	ACTIVE	SOT-23	DBV	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DBVTG4	ACTIVE	SOT-23	DBV	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKR	ACTIVE	SC70	DCK	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKRE4	ACTIVE	SC70	DCK	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKRG4	ACTIVE	SC70	DCK	5	3000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKT	ACTIVE	SC70	DCK	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKTE4	ACTIVE	SC70	DCK	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DCKTG4	ACTIVE	SC70	DCK	5	250	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DRLR	ACTIVE	SOT	DRL	5	4000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DRLRG4	ACTIVE	SOT	DRL	5	4000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DRY2	ACTIVE	SON	DRY	6	5000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DRYR	ACTIVE	SON	DRY	6	5000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	
SN74AUP1G04DSFR	ACTIVE	SON	DSF	6	5000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	



## **PACKAGE OPTION ADDENDUM**

21-May-2012

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/ Ball Finish	MSL Peak Temp <sup>(3)</sup>	Samples (Requires Login)
SN74AUP1G04YFPR	ACTIVE	DSBGA	YFP	4	3000	Green (RoHS & no Sb/Br)	SNAGCU	Level-1-260C-UNLIM	

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

# PACKAGE MATERIALS INFORMATION

www.ti.com 21-May-2012

### TAPE AND REEL INFORMATION

### **REEL DIMENSIONS**



### **TAPE DIMENSIONS**



A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

### TAPE AND REEL INFORMATION

\*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74AUP1G04DBVR	SOT-23	DBV	5	3000	178.0	9.0	3.23	3.17	1.37	4.0	8.0	Q3
SN74AUP1G04DCKR	SC70	DCK	5	3000	180.0	9.2	2.3	2.55	1.2	4.0	8.0	Q3
SN74AUP1G04DCKR	SC70	DCK	5	3000	178.0	9.2	2.4	2.4	1.22	4.0	8.0	Q3
SN74AUP1G04DCKT	SC70	DCK	5	250	178.0	9.0	2.4	2.5	1.2	4.0	8.0	Q3
SN74AUP1G04DRLR	SOT	DRL	5	4000	180.0	8.4	1.98	1.78	0.69	4.0	8.0	Q3
SN74AUP1G04DRY2	SON	DRY	6	5000	180.0	9.5	1.6	1.15	0.75	4.0	8.0	Q3
SN74AUP1G04DRYR	SON	DRY	6	5000	180.0	9.5	1.15	1.6	0.75	4.0	8.0	Q1
SN74AUP1G04DSFR	SON	DSF	6	5000	180.0	9.5	1.16	1.16	0.5	4.0	8.0	Q2
SN74AUP1G04YFPR	DSBGA	YFP	4	3000	178.0	9.2	0.89	0.89	0.58	4.0	8.0	Q1

www.ti.com 21-May-2012



\*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74AUP1G04DBVR	SOT-23	DBV	5	3000	180.0	180.0	18.0
SN74AUP1G04DCKR	SC70	DCK	5	3000	205.0	200.0	33.0
SN74AUP1G04DCKR	SC70	DCK	5	3000	180.0	180.0	18.0
SN74AUP1G04DCKT	SC70	DCK	5	250	180.0	180.0	18.0
SN74AUP1G04DRLR	SOT	DRL	5	4000	202.0	201.0	28.0
SN74AUP1G04DRY2	SON	DRY	6	5000	180.0	180.0	30.0
SN74AUP1G04DRYR	SON	DRY	6	5000	180.0	180.0	30.0
SN74AUP1G04DSFR	SON	DSF	6	5000	180.0	180.0	30.0
SN74AUP1G04YFPR	DSBGA	YFP	4	3000	220.0	220.0	35.0

#### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

**Applications** 

Automotive and Transportation www.ti.com/automotive

e2e.ti.com

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

		•	
Amplifiers	amplifier.ti.com	Communications and Telecom	www.ti.com/communications
Data Converters	dataconverter.ti.com	Computers and Peripherals	www.ti.com/computers
DLP® Products	www.dlp.com	Consumer Electronics	www.ti.com/consumer-apps
DSP	dsp.ti.com	Energy and Lighting	www.ti.com/energy
Clocks and Timers	www.ti.com/clocks	Industrial	www.ti.com/industrial
Interface	interface.ti.com	Medical	www.ti.com/medical
Logic	logic.ti.com	Security	www.ti.com/security
Power Mgmt	power.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video

RFID <u>www.ti-rfid.com</u>
OMAP Mobile Processors www.ti.com/omap

**Products** 

Audio

Wireless Connectivity www.ti.com/wirelessconnectivity

www.ti.com/audio

TI E2E Community Home Page

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2012, Texas Instruments Incorporated