



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: B006-004-R

### KVM Switch - 4-Port Desktop KVM Switch (USB)

#### Highlights

- USB Connections on both Console and Server side
- P758-Series KVM Cable kit required to connect to a computer
- Push Button switching on the front of the unit
- Built-in 2-Port USB hub shares two USB peripherals between attached systems
- OS independent operation - use with PCs or MACs



#### Description

Tripp Lite's 4-port Desktop USB KVM Switch is the optimal solution for controlling up to 4 USB computers from one keyboard, mouse, and monitor. It features keyboard and mouse emulation for error-free boot-ups and works on all operating systems. This device also supports 180MHz video resolutions up to 1920 x 1440 pixels without any noticeable degradation. It features a compact design that does not require external power, software, or complicated set-up procedures.

#### Applications

- Small Office/Home Office (SOHO). Control up to 4 USB computers from a single keyboard, mouse, and monitor.

#### Package Includes






- B006-004-R 4-port USB KVM Switch
- Instruction manual with warranty information

#### Features

- Control up to 4 USB computers from a single keyboard, mouse and monitor
- Console Ports: HD15 Female (Monitor) and 2 USB A Female (Keyboard/Mouse)
- Computer Ports: 4 HD15 Male (Monitor) and 4 USB B Female (Dual Keyboard/Mouse)
- Includes 2 USB A Female ports for sharing of USB peripherals between connected computers
- 2 LEDs per port; one indicates when the computer is connected & on, the other indicates when the computer has been selected
- Supports 180MHz video resolutions up to 1920 x 1440
- Supports VGA, SVGA, or Multisync monitors
- Does not require external power, software, or complicated set-up procedures
- Select a computer via front panel push-buttons
- Includes autoscan feature
- Keyboard and mouse emulation for dependable computer boot-up
- Compatible with all operating systems
- Compatible with most mice; including scroll mice

#### Specifications

---

OVERVIEW	
# Of Users	1
Console	No
Port Control	Push Buttons
Max CPU	4
Product Rear View	B006-004-R-rear.pdf
Cat5 KVM Switch	No
IP Remote Access	NO
PHYSICAL	
Shipping weight (lbs)	3.5
Unit weight (lbs)	3
Style	Desktop
LCD Monitor (in.)	Not Applicable
ENVIRONMENTAL	
BTUs	50Hz, 2.7 / 60Hz, 2.4
CONNECTIONS	
Ports	4
Other Ports	 (x2) USB A (Female)
Computer/Server Ports - Port 1	 HD15 (Male)
Computer/Server Ports - Port 2	 USB B (Female)
Local Console Ports - Port 1	 HD15 (Female)
Local Console Ports - Port 2	 (x2) USB A (Female)

## Related Items

### Required Products

Related Model	Description	Qty.
<a href="#">P758-006</a>	6-ft. KVM Switch USB Cable Kit for B006-VU4-R	1

### Optional Products

Related Model	Description	Qty.
<a href="#">P758-010</a>	10-ft. KVM Switch USB Cable Kit for B006-VU4-r	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=2024](http://www.tripplite.com/en/products/model.cfm?txtModelID=2024).

---

Copyright © 2012 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.